

FEATURES

- ◆ Complete speaker assembly
- ◆ 6" hanging back box
- ◆ 10 watt transformer
- ◆ Heavy duty 10 oz 1" voice coil
- ◆ Easy installation

APPLICATIONS

- ◆ Open ceiling retail outlets
- ◆ Warehouses



DESCRIPTION

The E600 series speaker/enclosure assembly is designed for high intelligibility, paging and foreground applications. Smooth response is obtained with the use of a heavy duty 10 oz. 1" voice coil, 4" speaker. A large 10-watt transformer assures low loss. The transformer is mounted by an aluminum plate to isolate the transformer/magnet flux interaction to ensure high intelligibility at high levels. The metal enclosure is both rugged and unobtrusive. The E600CX401T10 requires minimal assembly time. All is pre-mounted for ease of installation.

SPECIFICATIONS

Speaker

Diameter	4"
Magnet Weight	10 oz.
Frequency Response	75 - 16kHz
Voice coil diameter	1"
Impedance	8 ohms
Sensitivity (1 watt/1 meter)	89 dB average
Power Handling	20 watts

70/25 volt transformer - Primary Taps

70V	.62, 1.25, 2.5, 5, 10
25V	.62, 1.25, 2.5, 5, 10

Back Box

Size	6" diameter, 6" high, 1/4" mounting hole diameter
Colour	Beige